



Uninterruptible Power Supply

BBONE 2400VA
BBONE 1200VA



BBONE-024S+
(Excl Batteries)

BBONE-012S+ (Excl Battery)

Features

- Simulated sine wave inverter
- Wide input voltage range
- 10 A or 20 A standard AC charging current
- LCD display for comprehensive information
- Overload, short circuit and reverse polarity protection

MODEL	BBONE-012S+	BBONE-024S+
CAPACITY	1200VA/ 720W	2400VA/ 1440W
INPUT		
Voltage	230 VAC	
Acceptable Voltage Range	90-280 VAC	
Frequency	50 Hz/60 Hz (Auto sensing)	
OUTPUT		
AC Voltage Regulation (Batt. Mode)	± 10%	
Efficiency (Peak)	82%	85%
Transfer Time	20 ms typical	
Waveform (Batt. Mode)	Simulated sine wave	
BATTERY		
Battery Type and Numbers	12 V 100Ah x 1 (*Optional)	12 V 100Ah x 2 (*Optional)
PROTECTION		
Full Protection	Overload, short circuit and polarity reserve protection	
PHYSICAL		
Dimension	370mm (W)x310(D) x400(H)	370mm mm (W)x 490mm (D) x 400mm (H)
OPERATING ENVIRONMENT		
Humidity	0 to 90% Relative Humidity(Non-condensing)	
Operating Temperature	0°C to 40°C	
Storage Temperature	-15°C to 50°C	

* Product specifications are subject to change without further notice

E. & O.E.

***NB BBone-012S+ / BBone-024S+ EXCLUDED Batteries**

Distributed by



www.mecer.co.za
www.mustek.co.za

Johannesburg
Tel: 011 237 1000

Cape Town
Tel: 021 413 3000

Durban
Tel: 031 534 7000

Bloemfontein
Tel: 051 405 0400

Port Elizabeth
Tel: 041 397 8700

Kimberley
Tel: 053 831 1571

Gauteng
Tel: 011 237 1000

W Cape
Tel: 021 413 3000

KwaZulu-Natal
Tel: 041 534 7000

E Cape
Tel: 041 397 8700

Free State
Tel: 051 405 0400

N Cape
Tel: 053 831 1571

Mpumalanga
Tel: 013 752 6027

Nelspruit
Tel: 013 752 6027

Kenya
Mustek East Africa Ltd.
Tel: +254 020 3752175-9

Limpopo
Tel: 015 298 8571

North West
Tel: 018 381 5938